

# LUMISTAR

## LS-28-DRS Advanced Technology Dual Receiver/Combiner Unit Data Sheet

The Lumistar LS-28-DRS Rack Mount Dual Receiver/Combiner System, shown with optional external 1U Keyboard/Display, offers a low-cost high-performance COTS solution for a modern Telemetry Ground Station Receiving System.

The LS-28-DRS is an advanced technology “Dual” Receiver/Combiner employing sophisticated fourth generation Digital Signal Processing (DSP) technologies. The LS-28-DRS supports independent two channel reception and/or combining of up to four RF bands, such as E, S, lower/upper-L, P, K, or custom bands up to 3 GHz) The RF inputs are processed by the Lumistar LS-27 series dual channel quad band PCI-based tuner card that acquires and downconverts the signals to a 70 MHz intermediate frequency (IF). These IF signals are then digitized by the LS-35-R two-channel digital IF receiver. The IF receiver offers pre-D combining or routes the data directly to a multi-mode dual demodulator for two independent channel operation. The digital multi-mode demodulation options include Multi-Symbol PCM/FM, SOQPSK, BPSK, QPSK, OQPSK, AQPSK, PCM/PM, Sub-carrier(s)). Demodulated data is bit synchronized to TTL and RS-422 data/clock outputs, including PCM code conversions. Optional post-D combining is available. Standard features such as Eye pattern and Constellation diagram displays, IF spectral displays, bit error reader and onboard 70 MHz modulator are included at no additional cost. Legacy demodulation of analog NTSC/PAL FM signals can be optionally included. Since telemetry data is not routed through the system’s PCI bus, the LS-28-DRS can process high data rate streams with no impact to the processing load of the CPU.



Unlike analog legacy Receivers, the LS-28-DRS is a true software-defined radio whose digital implementation is highly flexible and expandable. The unit provides single/dual/tri/quad band operation utilizing Lumistar’s “LS-27 series” dual channel/quad-band down converter in a single PCI slot. The IF receiver/combiner functionality is realized within a single PCI card state-of-the-art digital processing engine, which can operate as a single or dual channel receiver/combiner. The standard receiver processes data rates from 10 kbps to 30 Mbps for PCM/FM, 10 Kbps to 20 Mbps for BPSK & PCM/PM, and up to 30 Mbps for QPSK/OQPSK/SOQPSK. Higher data rates are available as an option. The LS-28-DRS sensitivity and adjacent channel interference performance is superior due to the analog IF “SAW” and digital “FIR” filtering method employed at the IF. By using this method, IF bandwidths are optimally set by software “as a function of data rate/PCM code/modulation format”, but can be selected by the user as desired. The digital Combiner utilizes our “S/N Ratio Measurement” firmware technique to provide a signal to noise improvement of at least 2.5 dB with equal signals near threshold level at the LS-28-DRS inputs. For optimal multi-path avoidance, the Combiner operates at fade “break frequencies” up to 50 KHz. Best source selection can also be performed via software. The performance of the LS-28-DRS is repeatable, day-after-day, year-after-year, from unit-to-unit. It requires no periodic calibration. Life cycle costs are greatly reduced because future upgrades (such as new modulation formats) or an improved DSP algorithm are all implemented via software and/or firmware via an on-site upgrade.

Lumistar, Inc.

2270 Camino Vida Roble Suite L

Carlsbad, CA 92011

PHONE: 760-431-2181

FAX: 760-431-2665

EMAIL: [sales@lumistar.net](mailto:sales@lumistar.net)

<http://www.lumi-star.com>

*Specifications are subject to change. Please verify the latest specifications at time of order.*

11-1-13

## SPECIFICATIONS:

### Down-Converter (2 Each):

RF Input Frequency	S-band	2200-2400 MHz
	NATO E-Band:	2185-2485 MHz
	Upper L-Band:	1710-1850 MHz
	Lower L-Band:	1435-1540 MHz
	P-band:	215-320 MHz
	K-band:	680-760 MHz
	N-band:	830-1130 MHz
	70 MHz pass thru	70 MHz
	<i>(Other RF bands available, please consult Lumistar)</i>	
Input Level:	+10 dBm to threshold	
Maximum Input Level:	+28 dBm (self-protection at startup for > +28 dBm)	
Tuner Resolution:	50 KHz	
Frequency Accuracy	0.001% typical, 0.002% max	
Noise Figure	8 dB (Maximum); 5 dB (Typical at threshold)	
IF Filters:	Software set by data rate, PCM code and modulation format User override available Eight SAW anti-alias pre-filters (0.25, 0.50, 1, 2, 5, 10, 20, 40 MHz) Precision digital FIR filtering employed at demodulation input	
Phase Noise:	Exceeds requirements for ARTM Tier II phase noise (-110 dBm typ at 100KHz)	
AGC Slope and Range	Programmable over any portion, -4V to +4V, Linear, Pos/Neg	
AGC Time Constants:	Selectable: 0.1, 1, 10, 100, 1000 mSec Programmable between 0.1 and 6500 mSec)	
RF Input AGC Range:	110 dB (+10 to -100 dBm)	
Input Compression:	+10 dBm	
IP3:	+15 dBm typical (output)	
AM Demodulation:	DC to 50 KHz, programmable output vs. AM depth typically 2V p-p for 50% modulation depth	
AM Filtering:	32 each lowpass filters, plus Bypass Mode	
Adj Channel Interference:	exceeds IRIG requirements, contact Lumistar for more information	
Bias "T" Power Supply:	up to +25V, 500 mA	

### Pre-D Combiner (1 Each):

Combiner Type:	Digital
	Combining algorithm based upon measured S/N for each channel
S/N Improvement:	2.5 dB typical (equal RF input levels near threshold)
Break Frequency:	50 KHz minimum for 30 dB fades

The digital combiner employs a DSP-based algorithm to provide best combined signal based upon real time CH1 v. CH2 Eb/No measurements. The combiner does not require AGC information for combining decision, and it is not a simple "best-source selector but a true diversity combiner. The combiner operates with a break frequency of > 50 KHz with worst case multipath fade scenarios (such as -sin/sin AM for CH1 vs. CH2). The combiner supports polarization, frequency and spatial diversity applications.

### Demodulator Outputs (2 Each)

# LUMISTAR

Demodulation Formats	Options include Multi-symbol PCM/FM, PCM/PM, BPSK, QPSK, SOQPSK, OQPSK, AQPSK, Analog FM for NTSC/PAL Video, Sub-carrier(s)
Data Rates	10 kbps – 30 Mbps (Multi-Symbol PCM/FM) 10 kbps – 20 Mbps (BPSK, PCM/PM) 1 Mbps to 30 Mbps (QPSK, OQPSK, AQPSK, SOQPSK) <i>(Higher data rates are available, please consult Lumistar)</i>
Bit Syncs:	Two Independent Data/Clock Outputs for each channel CH1/CH2/Combined available (any two at a time) TTL and RS-422 available simultaneously on each channel >3V peak in to 50 ohms
Code Conversion:	NRZ-L, M, S and Bi- $\Phi$ L, M, S; DM-M, S; MDM-M, S

## Standard Features:

Internal IF Modulator:	Internal 50-90 MHz Modulator for loop-back self-test of the receiver. Power output from 0 to -80 dBm. Formats include PCM/FM, PCM/PM, BPSK, QPSK, OQPSK, SOQPSK and Multi-h CPM, with data rates from 10 bps to 10 Mbps (for FM/PM/BPSK) and 20 Mbps for all QPSK formats and Multi-H CPM. Includes precision calibrated noise feature, output code selection (NRZ-L/M/S, Bi-Phase L/M/S, DMM/S, and RNRZ15), external modulation input, internal PRN pattern generation, adjustable deviation, and Convolutional encoding.
Multi-symbol PCM/FM	Improves BER performance by approx. 2.5 dB vs. standard PCM/FM
Constellation Displays	for all PSK formats
Eye Pattern Displays	for PCM/FM format
Bit Error Rate Readers:	One each per input channel, can be connected to Pre-D combiner
IF Spectrum Displays:	Displays 70 MHz IF Spectrum, has typical spectrum analyzer controls and capabilities (such as Span, Averaging, Ref level, max hold, clear/write, etc...). All displays can be captured via "Screen-Shot" hardcopy feature, available in JPG file format.

## Optional Features:

- Multimode demodulation formats
- PCM/FM only (-M1), SOQPSK (-M2), PCM/FM and SOQPSK only (-M6)
- PCM/FM, BPSK, QPSK, OQPSK, SOQPSK, and PM (-M3)
  - Other demodulation options available, lease consult factory
- Viterbi decoding (-V2)
- Sub-carrier (-S2)
- AQPSK (-A2)
- Post-Diversity Combining (-O)
- Viterbi and Reed / Solomon Decoding
- FPGA upgrade (for additional I/O)

## Environmental:

Operating Temperature            0° to +50° C

Lumistar, Inc.

2270 Camino Vida Roble Suite L

Carlsbad, CA 92011

PHONE: 760-431-2181

FAX: 760-431-2665

EMAIL: [sales@lumistar.net](mailto:sales@lumistar.net)

<http://www.lumi-star.com>

*Specifications are subject to change. Please verify the latest specifications at time of order.*

11-1-13

Non-Operating Temperature	-25° to +70° C
Operating Humidity	0 to 90% (Non-condensing)
Non-Operating Humidity	Protect from excessive moisture and contamination
Operational Scenario:	Rack mount, ground-based, with sufficient cooling in rack (Option for airborne applications, please consult Lumistar)

**Physical:**

Size	4U Rack Mount Chassis (19" W x 23" D x 7" H)
Weight	40 lbs (18.1 Kg) typical
Power Supply	115 V/230 V Auto-sensing – 100W
Computer I/O:	Passive SBC backplane, 4 Gbyte RAM typ, Quad-Core Processor, Dual TCP/IP, Dual VGA, USB (2 min), PS2, Windows XP

**Ordering Information:**

<b>Model Number Examples:</b>	LS-28-DRS-M1	(PCM/FM format only)
	LS-28-DRS-M2	(SOQPSK only)
	LS-28-DRS-M6	(PCM/FM & SOQPSK formats only)
	LS-28-DRS-M6-V2	(PCM/FM & SOQPSK, with Viterbi)



**Rear View of Chassis  
LS-28-QRS/DRS Series Rack Mount Receiver/Combiner Systems**

*For additional information please see data sheet for LS-35-R and LS-27-D3*